
TOSHIBA BIPOLAR LINEAR INTEGRATED CIRCUIT SILICON MONOLITHIC

### TA8637BP

#### VHF MODULATOR FOR VCR OR VDP

#### **FEATURES**

- Video clamp
- White clip
- Main carrier oscillator
- Main carrier attenuator
- Video Modulator
- Sound Modulator
- Sound FM Modulator
- **Channel Switch**
- Low power operation
- Adjustable output level and V/A ratio with external resistance.
- Minimum number of external parts required.
- Regulator circuit is included.
- Operating voltage range : 4.5V~5.5V, Typ. 5V
- Suggested operating voltage: 4.75V~5.25V, Typ. 5V



Weight : 1.11g (Typ.)

and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.


The products described in this document are subject to foreign exchange and foreign trade control laws.

The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.

The information contained herein is subject to change without notice.

TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating the standard standard products are used within specified operating the standard standard specified operating the specified operat and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.

## **BLOCK DIAGRAM & APPLICATION CIRCUIT**



(\*) See SAW Resonator Technical Data.

#### **MAXIMUM RATINGS** (Ta = 25°C)

CHARACTERISTIC	SYMBOL	RATING	UNIT
Supply Voltage	Vcc	7	V
Power Dissipation	P <sub>D</sub> (Note)	750	mA
Input Signal Voltage	e <sub>in</sub>	2.5	V <sub>p-p</sub>
Input Voltage at Pin 7	V <sub>in</sub>	GND - 0.3~V <sub>CC</sub> + 0.3	V
Operating Temperature	T <sub>opr</sub>	<b>− 10~70</b>	°C
Storage Temperature	T <sub>stg</sub>	<b>-</b> 55∼150	°C

(Note) Derated above  $Ta = 25^{\circ}C$  in the proportion of  $6mW/^{\circ}C$ .

#### **ELECTRICAL CHARACTERISTICS** ( $V_{CC} = 5.0V$ , Ta = 25°C)

	1.66		,					
CHARACTERISTIC	SYMBOL	TEST CIR- CUIT	TEST CONDITION	MIN.	TYP.	MAX.	UNIT	
Supply Current	<sup>I</sup> CC	_	$S_1 = 2$ , $S_2 = 1$ , $S_3 = 2$	10	14	20	mA	
Video RF Output Level	V <sub>0</sub> (f <sub>p1</sub> )	_	$S_2 = 1$ , $S_3 = 2$ (Note 1) $V_{i,1}$ : No input signal	S <sub>1</sub> = 2	90	92	94	dΒμV
•	V <sub>o</sub> (f <sub>p2</sub> )	—	V <sub>o1</sub> : Output level	S <sub>1</sub> = 1				
Video RF Output Level Temperature Drift	△V <sub>0</sub> (f <sub>p1</sub> )	_	$V_O (f_{p1}) (Ta = -10~70^{\circ}C)$ - $V_O (f_{p1}) (Ta = 25^{\circ}C)$		_	±2	dB	
	△V <sub>0</sub> (f <sub>p2</sub> )		$V_O (f_{p2}) (Ta = -10 \sim 70^{\circ}C)$ - $V_O (f_{p2}) (Ta = 25^{\circ}C)$					
Video Modulation	m <sub>p1</sub>		$S_2 = 1$ , $S_3 = 2$	S <sub>1</sub> = 2			82	%
Factor	m <sub>p2</sub>		$V_{i1} = 0.45V_{p-p}$ , white	S <sub>1</sub> = 1		77	<u> </u>	, 3
Video Modulation Factor Temperature	∆m <sub>p1</sub>	1	$m_{p1}$ (Ta = -10~70°C) - $m_{p1}$ (Ta = 25°C)	_	_	±3	%	
Stability	⊿m <sub>p2</sub>	1	$m_{p2}$ (Ta = -10~70°C) - $m_{p2}$ (Ta = 25°C)					
Video Modulation Factor Difference	∆mp	1	m <sub>p1</sub> – m <sub>p2</sub>	_	_	± 1	%	
Max. Video Modulation Factor	m <sub>p2</sub> (Max.)	1	$S_1 = 1$ , $S_2 = 1$ , $S_3 = 2$ $V_{i,1} = 2.0V_{p-p}$ , white	89	94	98	%	
Max. Video Modulation Temperature Drift	⊿m <sub>p2</sub> (Max.)	1	Ta = - 10~70°C m <sub>p2</sub> (Max	89	94	98	%	
Defferential Gain	DG <sub>1</sub>		S <sub>2</sub> = 1, S <sub>3</sub> = 2,	S <sub>1</sub> = 2	_	± 2	± 5	%
	DG <sub>2</sub>	2	$V_{i1} = 0.45V_{p-p}$ , Stair case, (Note 2)	S <sub>1</sub> = 1				
Defferential Phase	DP <sub>1</sub>	2	$S_2 = 1$ , $S_3 = 2$ , $V_{i,1} = 0.45 V_{p-p}$ ,	S <sub>1</sub> = 2	_   +2	± 2	± 5	o
	DP <sub>2</sub>		Stair case, (Note 2) $S_1 = 1$					
Sound RF Output Level	V <sub>o</sub> (f <sub>s1</sub> ) V <sub>o</sub> (f <sub>s2</sub> )	_	$S_2 = 1, S_3 = 2$ (Note 1) $S_1 = 2$ $V_{O3}$ : Sound RF level $S_1 = 1$		81	83	86	$dB\muV$
Sound FM Temperature Drift	Δf <sub>S</sub>	_	$S_1 = 1$ , $S_2 = 2$ , $S_3 = 2$ (Note 3) $f_s$ (Ta = 0~60°C) – $f_s$ (Ta = 25°C)		_	_	± 10	kHz
Sound FM Modulation Sensitivity	$\beta_{S}$	_	$S_1 = 1, S_2 = 2, S_3 = 1$ (N	lote 4)	I	0.43	_	kHz/ mV
Sound Total Harmonic Distortion	THD	_	$S_1 = 1$ , $S_2 = 2$ , $S_3 = 3$ $V_{i2} = 1$ kHz (N	lote 5)	_	0.2	1.0	%

(Note 1) Measure RF level by spectrum analyzer (Input impedance = 50) and calculate measurement data  $V_{\rm O}$  (dBm) by

Output Level (dB $\mu$ V) = V<sub>O</sub> + 107 + 16 (dB $\mu$ V)

- (Note 2) Measure after that demodulated by the standard demodulator (For example Tektronix 1450).
- (Note 3) Adjust a sound FM center frequency to 4.500MHz at  $Ta = 25^{\circ}C$ , then measure a frequency drift at  $Ta = 0 \sim 60^{\circ}C$  for at  $Ta = 25^{\circ}C$ . This spec ( $\Delta f_s$ ) does not include TANK temperature coefficiency.
- (Note 4) Connect Va + 0.2 (V) and Va 0.2 (V) to V<sub>1</sub> (Va; #6 terminals open voltage) then measure each frequency and calculate by


$$\beta_s = \frac{\text{Frequency difference between V}_1 = \text{Va} + 0.2 \text{ and V}_2 = \text{Va} - 0.2}{0.4}$$


(Note 5) Adjust  $V_{i2}$  level so that FM deviation become  $\pm 20 kHz$ , then measure THD after that demodulate by standard demodulator (for example tektronix 1450)

Input wave form White signal


Stair case signal


APL 50% sub carrier 20 IRE








#### **TEST CIRCUIT**











#### SOUND, VIDEO MODULATION RANK CLASSFICATION


RANK	SOUND FM MODULATION SENSITIVITY				VIDEO MODULATION FACT				MARK
NAINK	MIN	TYP.	MAX	UNIT	MIN	TYP.	MAX	UNIT	IVIANK
1	0.36	0.39	0.42	kHz/mV	72	75	78		Green
2	0.39	0.43	0.46		72	75	78		Yellow
3	0.44	0.48	0.52		72	75	78	%	Red
4	0.36	0.39	0.42		76	79	82	70	Blue
5	0.39	0.43	0.46		76	79	82		Orange
6	0.44	0.48	0.52		76	79	82		Purple


(Note) TA8637BP does not receive the rank classification specification when ordering.

Unit: mm

# OUTLINE DRAWING DIP16-P-300-2.54A

□ 8





Weight: 1.11g (Typ.)